

Acue Lighting Color Blaster LED Pixel Bar IP65

<u>DMX 2 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~5	No Function
	6~16	Red
	17~27	Green
	28~38	Blue
	39~49	Yellow
	50~60	Pink
	61~71	Cyan
	72~82	White
	83~93	Jump Effect 1
	94~104	Jump Effect 2
	105~155	Jump Effect 3
	166~126	Jump Effect 4
	127~137	Jump Effect 5
	138~148	Jump Effect 6
	149~159	Jump Effect 7
	160~170	Jump Effect 8
	171~181	Loop Effect 1-8
	182~192	Red Shade Effect
	193~203	Green Shade Effect
	204~214	Blue Shade Effect
215~225	Pink Shade Effect	
226~236	Yellow Shade Effect	
237~247	Loops Red to Yellow Shade Effect	
248~255	Sound Active	
Channel 2	0~255	Speed: Slow to Fast

<u>DMX 3 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	R Dimmer: Dark to Bright
Channel 2	0~255	G Dimmer: Dark to Bright
Channel 3	0~255	B Dimmer: Dark to bright

<u>DMX 5 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Master Dimmer: Dark to Bright
Channel 2	0~255	R Dimmer: Dark to Bright
Channel 3	0~255	G Dimmer: Dark to Bright
Channel 4	0~255	B Dimmer: Dark to Bright
Channel 5	7~255	RGB Strobe: Slow to Fast

DMX 8 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Master Dimmer: Dark to Bright
Channel 2	7~255	RGB Strobe: Slow to Fast
Channel 3		MACROS / EFFECTS
	0~5	No Function
	6~15	Effects 1-13
	16~25	Channel 1: Dimmer
	26~35	Channel 2: Strobe Effect
	36~45	Channel 5: Color Change
	46~55	Channel 6-8: Color Change
	56~65	Macro 1
	66~75	Macro 2
	76~85	Macro 3
	86~95	Macro 4
	96~105	Macro 5
	106~115	Macro 6
	116~125	Macro 7
	126~135	Macro 8
	136~145	Jump Effect 1
	146~155	Jump Effect 2
	156~165	Jump Effect 3
	166~175	Jump Effect 4
	176~185	Jump Effect 5
186~195	Jump Effect 6	
196~205	Jump Effect 7	
206~215	Jump Effect 8	
216~225	Loop Jump Effects 1-8	
226~235	Yellow Shade Effect	
236~245	Loops Red to Yellow Shade Effect	
246~255	Sound Active	
Channel 4	0~255	Effects Speed: Slow to Fast
Channel 5	0~255	Color Select
Channel 6	0~255	R Dimmer: Dark to Bright
Channel 7	0~255	G Dimmer: Dark to Bright
Channel 8	0~255	B Dimmer: Dark to Bright

DMX 42 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	1 R Dimmer: Dark to Bright
Channel 2	0~255	1 G Dimmer: Dark to Bright
Channel 3	0~255	1 B Dimmer: Dark to Bright
Channel 4	0~255	2 R Dimmer: Dark to Bright
Channel 5	0~255	2 G Dimmer: Dark to Bright
Channel 6	0~255	2 B Dimmer: Dark to Bright
Channel 7	0~255	3 R Dimmer: Dark to Bright
Channel 8	0~255	3 G Dimmer: Dark to Bright
Channel 9	0~255	3 B Dimmer: Dark to Bright
Channel 10	0~255	4 R Dimmer: Dark to Bright
Channel 11	0~255	4 G Dimmer: Dark to Bright
Channel 12	0~255	4 B Dimmer: Dark to Bright
Channel 13	0~255	5 R Dimmer: Dark to Bright
Channel 14	0~255	5 G Dimmer: Dark to Bright
Channel 15	0~255	5 B Dimmer: Dark to Bright
Channel 16	0~255	6 R Dimmer: Dark to Bright
Channel 17	0~255	6 G Dimmer: Dark to Bright
Channel 18	0~255	6 B Dimmer: Dark to Bright

Channel 19	0~255	7 R Dimmer: Dark to Bright
Channel 20	0~255	7 G Dimmer: Dark to Bright
Channel 21	0~255	7 B Dimmer: Dark to Bright
Channel 22	0~255	8 R Dimmer: Dark to Bright
Channel 23	0~255	8 G Dimmer: Dark to Bright
Channel 24	0~255	8 B Dimmer: Dark to Bright
Channel 25	0~255	9 R Dimmer: Dark to Bright
Channel 26	0~255	9 G Dimmer: Dark to Bright
Channel 27	0~255	9 B Dimmer: Dark to Bright
Channel 28	0~255	10 R Dimmer: Dark to Bright
Channel 29	0~255	10 G Dimmer: Dark to Bright
Channel 30	0~255	10 B Dimmer: Dark to Bright
Channel 31	0~255	11 R Dimmer: Dark to Bright
Channel 32	0~255	11 G Dimmer: Dark to Bright
Channel 33	0~255	11 B Dimmer: Dark to Bright
Channel 34	0~255	12 R Dimmer: Dark to Bright
Channel 35	0~255	12 G Dimmer: Dark to Bright
Channel 36	0~255	12 B Dimmer: Dark to Bright
Channel 37	0~255	13 R Dimmer: Dark to Bright
Channel 38	0~255	13 G Dimmer: Dark to Bright
Channel 39	0~255	13 B Dimmer: Dark to Bright
Channel 40	0~255	14 R Dimmer: Dark to Bright
Channel 41	0~255	14 G Dimmer: Dark to Bright
Channel 42	0~255	14 B Dimmer: Dark to Bright

DMX 44 Channel		
Channel	DMX Range	Function
Channel 1	0~255	RGB Dimmer: Dark to Bright
Channel 2	7~255	RGB Strobe: Slow to Fast
Channel 3	0~255	1 R Dimmer: Dark to Bright
Channel 4	0~255	1 G Dimmer: Dark to Bright
Channel 5	0~255	1 B Dimmer: Dark to Bright
Channel 6	0~255	2 R Dimmer: Dark to Bright
Channel 7	0~255	2 G Dimmer: Dark to Bright
Channel 8	0~255	2 B Dimmer: Dark to Bright
Channel 9	0~255	3 R Dimmer: Dark to Bright
Channel 10	0~255	3 G Dimmer: Dark to Bright
Channel 11	0~255	3 B Dimmer: Dark to Bright
Channel 12	0~255	4 R Dimmer: Dark to Bright
Channel 13	0~255	4 G Dimmer: Dark to Bright
Channel 14	0~255	4 B Dimmer: Dark to Bright
Channel 15	0~255	5 R Dimmer: Dark to Bright
Channel 16	0~255	5 G Dimmer: Dark to Bright
Channel 17	0~255	5 B Dimmer: Dark to Bright
Channel 18	0~255	6 R Dimmer: Dark to Bright
Channel 19	0~255	6 G Dimmer: Dark to Bright
Channel 20	0~255	6 B Dimmer: Dark to Bright
Channel 21	0~255	7 R Dimmer: Dark to Bright
Channel 22	0~255	7 G Dimmer: Dark to Bright
Channel 23	0~255	7 B Dimmer: Dark to Bright
Channel 24	0~255	8 R Dimmer: Dark to Bright
Channel 25	0~255	8 G Dimmer: Dark to Bright
Channel 26	0~255	8 B Dimmer: Dark to Bright
Channel 27	0~255	9 R Dimmer: Dark to Bright
Channel 28	0~255	9 G Dimmer: Dark to Bright
Channel 29	0~255	9 B Dimmer: Dark to Bright
Channel 30	0~255	10 R Dimmer: Dark to Bright
Channel 31	0~255	10 G Dimmer: Dark to Bright
Channel 32	0~255	10 B Dimmer: Dark to Bright
Channel 33	0~255	11 R Dimmer: Dark to Bright
Channel 34	0~255	11 G Dimmer: Dark to Bright
Channel 35	0~255	11 B Dimmer: Dark to Bright
Channel 36	0~255	12 R Dimmer: Dark to Bright
Channel 37	0~255	12 G Dimmer: Dark to Bright
Channel 38	0~255	12 B Dimmer: Dark to Bright
Channel 39	0~255	13 R Dimmer: Dark to Bright
Channel 40	0~255	13 G Dimmer: Dark to Bright
Channel 41	0~255	13 B Dimmer: Dark to Bright
Channel 42	0~255	14 R Dimmer: Dark to Bright
Channel 43	0~255	14 G Dimmer: Dark to Bright

Channel 44	0~255	14 B Dimmer: Dark to Bright
------------	-------	-----------------------------