

# Acue Lighting Focus 8 LED Pinspot

<u>DMX 2 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	STROBE	
	0~31	LED Off
	32~63	LED On
	64~95	Strobe Effect 1: Slow to Fast
	96~127	Strobe Effect 2: Slow to Fast
	128~159	Pulse Effect: In Sequence
	160~191	LED On
	192~223	Random Strobe Effect: Slow to Fast
224~255	LED Off	

<u>DMX 4 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	STROBE	
	0~31	LED Off
	32~63	LED On
	64~95	Strobe Effect 1: Slow to Fast
	96~127	Strobe Effect 2: Slow to Fast
	128~159	Pulse Effect: In Sequence
	160~191	LED On
	192~223	Random Strobe Effect: Slow to Fast
224~255	LED Off	
CH3	BUILT-IN PROGRAMS	
CH4	0~14	No Function
	15~44	Program 1
	45~74	Program 2
	75~104	Program 3
	105~134	Program 4
	135~164	Program 5
	165~194	Program 6
	195~224	Program 7
	225~255	Program 8
0~255	Program Speed: Fast to Slow	

**DMX 8 Channel**

<b><u>Channel</u></b>	<b><u>DMX Range</u></b>	<b><u>Function</u></b>
CH1	0~255	LED 1 Dimmer: 0-100%
CH2	0~255	LED 2 Dimmer: 0-100%
CH3	0~255	LED 3 Dimmer: 0-100%
CH4	0~255	LED 4 Dimmer: 0-100%
CH5	0~255	LED 5 Dimmer: 0-100%
CH6	0~255	LED 6 Dimmer: 0-100%
CH7	0~255	LED 7 Dimmer: 0-100%
CH8	0~255	LED 8 Dimmer: 0-100%