

Acue Lighting Magic 9 IP Wireless

DMX 5 Channel		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	R Dimmer: Dark to Bright
Channel 2	0~255	G Dimmer: Dark to Bright
Channel 3	0~255	B Dimmer: Dark to Bright
Channel 4	0~255	W Dimmer: Dark to Bright
Channel 5	0~19	Normal Mode
	20~39	Dimming Curve: 1
	40~59	Dimming Curve: 2
	60~255	Dimming Curve: 3

DMX 9 Channel		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Master Dimmer: Dark to Bright
Channel 2	0~9	Strobe Off
	10~255	Shutter Strobe Speed: Slow to Fast
Channel 3	0~255	R Dimmer: Dark to Bright
Channel 4	0~255	G Dimmer: Dark to Bright
Channel 5	0~255	B Dimmer: Dark to Bright
Channel 6	0~255	W Dimmer: Dark to Bright
Channel 7	0~9	Dimmer Mode
	10~29	Color Selection
	30~49	Color Change Mode 1
	50~69	Color Change Mode 2
	70~89	Color Change Mode 3
	90~109	Red Strobe
	110~129	Green Strobe
	130~149	Blue Strobe
	150~169	Total Strobe
	170~209	Sound-active Mode 1
	210~229	Sound-active Mode 2
230~255	Sound-active Mode 3	
Channel 8	0~255	Function Control
Channel 9	0~19	Normal Mode
	20~39	Dimming Curve 1
	40~59	Dimming Curve 2
	60~255	Dimming Curve 3