

Acue Lighting Pixel 4 LED Bar

<u>DMX 2 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	COLOR & PROGRAMS	
	0~11	Off
	12~23	Red
	24~35	Green
	26~47	Blue
	48~59	Yellow
	60~71	Purple
	72~83	Cyan
	84~95	White
	96~107	Program 1
	108~119	Program 2
	120~131	Program 3
	132~143	Program 4
	144~155	Program 5
	156~167	Program 6
	168~179	Program 7
	180~191	Program 8
	192~203	Program 9
	204~215	Program 10
216~227	Program 11	
228~239	Program 12	
240~251	Program 13	
252~255	Sound-Active	
CH2	0~255	Program Speed / Sound-Active Sensitivity

<u>DMX 3 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	R Dimmer
CH2	0~255	G Dimmer
CH3	0~255	B Dimmer

DMX 4 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	R Dimmer
CH2	0~255	G Dimmer
CH3	0~255	B Dimmer
CH4	0~255	Master Dimmer

DMX 7 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	R Dimmer
CH2	0~255	G Dimmer
CH3	0~255	B Dimmer
CH4	COLOR & PROGRAMS	
	0~11	Off
	12~23	Red
	24~35	Green
	26~47	Blue
	48~59	Yellow
	60~71	Purple
	72~83	Cyan
	84~95	White
	96~107	Program 1
	108~119	Program 2
	120~131	Program 3
	132~143	Program 4
	144~155	Program 5
	156~167	Program 6
	168~179	Program 7
	180~191	Program 8
	192~203	Program 9
	204~215	Program 10
216~227	Program 11	
228~239	Program 12	
240~251	Program 13	
252~255	Sound-Active	
CH5	0~255	Program Speed / Sound-Active Sensitivity
CH6	STROBE	
	0~4	Off
	5~255	Speed
CH7	0~255	Master Dimmer

DMX 14 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	R Dimmer 1
CH2	0~255	G Dimmer 1
CH3	0~255	B Dimmer 1
CH4	0~255	R Dimmer 2
CH5	0~255	G Dimmer 2
CH6	0~255	B Dimmer 2
CH7	0~255	R Dimmer 3
CH8	0~255	G Dimmer 3
CH9	0~255	B Dimmer 3
CH10	0~255	R Dimmer 4
CH11	0~255	G Dimmer 4
CH12	0~255	B Dimmer 4
CH13	0~255	Strobe
CH14	0~255	Master Dimmer