

Acue Lighting LED Strobe Bar

<u>4 DMX Channel Mode</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Dimmer 0-100%
Channel 2	0~255	Shutter Strobe Speed: Slow to Fast
Channel 3	0~255	Auto Program 1
Channel 4	0~255	Auto Program 2

12 DMX Channel Mode

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Pixel 1 Dimmer
Channel 2	0~255	Pixel 2 Dimmer
Channel 3	0~255	Pixel 3 Dimmer
Channel 4	0~255	Pixel 4 Dimmer
Channel 5	0~255	Pixel 5 Dimmer
Channel 6	0~255	Pixel 6 Dimmer
Channel 7	0~255	Pixel 7 Dimmer
Channel 8	0~255	Pixel 8 Dimmer
Channel 9	0~255	Pixel 9 Dimmer
Channel 10	0~255	Pixel 10 Dimmer
Channel 11	0~255	Pixel 11 Dimmer
Channel 12	0~255	Pixel 12 Dimmer

16 DMX Channel Mode

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Dimmer 0-100%
Channel 2	0~255	Shutter Strobe Speed: Slow to Fast
Channel 3	0~255	Speed of Auto-run
Channel 4	0~255	Auto-run
Channel 5	0~255	Pixel 1 Dimmer
Channel 6	0~255	Pixel 2 Dimmer
Channel 7	0~255	Pixel 3 Dimmer
Channel 8	0~255	Pixel 4 Dimmer
Channel 9	0~255	Pixel 5 Dimmer
Channel 10	0~255	Pixel 6 Dimmer
Channel 11	0~255	Pixel 7 Dimmer
Channel 12	0~255	Pixel 8 Dimmer
Channel 13	0~255	Pixel 9 Dimmer
Channel 14	0~255	Pixel 10 Dimmer
Channel 15	0~255	Pixel 11 Dimmer
Channel 16	0~255	Pixel 12 Dimmer