

Acue Lighting

Magic 6 Wireless Par

<u>DMX 4 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	0~255	R Dimmer: 0-100%
CH3	0~255	G Dimmer: 0-100%
CH4	0~255	B Dimmer: 0-100%

<u>DMX 8 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	0~255	R Dimmer: 0-100%
CH3	0~255	G Dimmer: 0-100%
CH4	0~255	B Dimmer: 0-100%
CH5	0~255	WW Dimmer: 0-100%
CH6	0~255	Strobe
	FUNCTIONS	
	0~8	Dimmer Off

CH7	9~50	Static Mixing Mode: 15 Colors
	51~100	Color Jump Mode
	101~150	Color Pulse Mode
	151~200	Color Gradient Mode
	201~220	Sound-Active 1
	221~240	Sound-Active 2
	241~255	Sound-Active 3
CH8	0~255	Function Speed