

# Acue Lighting Magic 54 RGBWW

<b>DMX 8 Channel Model(A001)</b>		
<b>Channel</b>	<b>DMX Range</b>	<b>Function</b>
Channel 1	0~255	Master Dimmer: Dark to Bright
Channel 2	0~255	R Dimmer: Dark to Bright
Channel 3	0~255	G Dimmer: Dark to Bright
Channel 4	0~255	B Dimmer: Dark to Bright
Channel 5	0~255	WW Dimmer: Dark to Bright
Channel 6	0~255	Shutter Strobe Speed: Slow to Fast
Channel 7	0~50	No Function
	51~100	Color Selection
	101~150	Colors Jump Change
	151~200	Color Fade
	201~250	Colors Pulse Change
Channel 8	251~255	Sound-active
Channel 8	0~255	Function Speed: Slow to Fast

<b>DMX 4 Channel Model(D001)</b>		
<b>Channel</b>	<b>DMX Range</b>	<b>Function</b>
Channel 1	0~255	R Dimmer: Dark to Bright
Channel 2	0~255	G Dimmer: Dark to Bright
Channel 3	0~255	B Dimmer: Dark to Bright
Channel 4	0~255	WW Dimmer: Dark to Bright