

Acue Lighting COB LED Blinder 2 WW

<u>DMX 6 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Dimmer 1: 0-100%
CH2	0~255	Dimmer 2: 0-100%
CH3	0~255	Master Dimmer: 0-100%
CH4	0~255	Strobe
CH5	DIMMER MODES	
	0~50	Regular Dimmer Selection (Default)
	51~101	Linear Dimmer: 0-100%
	102~152	Square Wave Dimmer
	153~204	Inverse Wave Dimmer
205~255	S-Curve Dimmer	
CH6	DIMMER DURATION	
	0~50	0 Seconds
	51~101	1 Second
	102~152	2 Seconds
	153~203	3 Seconds
204~255	5 Seconds	

<u>DMX 8 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Dimmer 1: 0-100%
CH2	0~255	Dimmer 2: 0-100%
CH3	0~255	Master Dimmer: 0-100%
CH4	0~255	Strobe
CH5	DIMMER MODES	
	0~50	Regular Dimmer Selection (Default)
	51~101	Linear Dimmer: 0-100%
	102~152	Square Wave Dimmer
	153~204	Inverse Wave Dimmer
205~255	S-Curve Dimmer	
CH6	DIMMER DURATION	
	0~50	0 Seconds
	51~101	1 Second
	102~152	2 Seconds
	153~203	3 Seconds
204~255	5 Seconds	
CH7	0~255	Color Scroll
CH8	0~255	Color Fade