

Acue Lighting Phantom 19x15W

<u>DMX 14 Channels</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Pan
CH2	0~255	Pan Fine
CH3	0~255	Tilt
CH4	0~255	Tilt Fine
CH5	0~255	Pan / Tilt Speed
CH6	RESET	
	50~70	Pan Reset
	71~90	Tilt Reset
	91~110	Zoom Reset
	200~255	System Reset
CH7	0~255	Master Dimmer: 0-100%
CH8	STROBE	
	0~3	No Function
	4~128	Speed: Slow to Fast
	129~255	Random Strobe: Slow to Fast
CH9	0~255	Red: Dark to Bright
CH10	0~255	Green: Dark to Bright
CH11	0~255	Blue: Dark to Bright
CH12	0~255	White: Dark to Bright
CH13	0~255	Color Mixing
CH14	0~255	Zoom

<u>DMX 25 Channels</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	STROBE	
	0~3	No Function
	4~128	Speed: Slow to Fast
	129~255	Random Strobe: Slow to Fast
CH2	0~255	Master Dimmer: 0-100%
CH3	0~255	Zoom
CH4	0~255	Pan
CH5	0~255	Pan Fine
CH6	0~255	Tilt
CH7	0~255	Tilt Fine
	RESET	

CH8	50~70	Pan Reset
	71~90	Tilt Reset
	91~110	Zoom Reset
	200~255	System Reset
CH9	LED FUNCTION	
	0~10	No Function
	11~80	Color Change
	81~123	Color Effect 1
	124~166	Color Effect 2
	167~209	Color Effect 3
	210~255	Color Effect 4
CH10	0~255	Red
CH11	0~255	Green
CH12	0~255	Blue
CH13	0~255	White
CH14	0~255	Color Mixing
CH15	0~255	Dimming Mode 1
CH16	0~255	Dimming Mode 2
CH17	0~255	Dimming Mode 3
CH18	0~255	Dimming Mode 4
CH19	0~255	Pan / Tilt Speed
CH20	BACKLIGHT STROBE	
	0~3	No Function
	4~128	Speed: Slow to Fast
	129~255	Random Strobe: Slow to Fast
CH21	0~255	Backlight Dimmer: 0-100%
CH22	BACKLIGHT LED FUNCTION	
	0~10	No Function
	11~80	Color Change
	81~123	Color Effect 1
	124~166	Color Effect 2
	167~209	Color Effect 3
	210~255	Color Effect 4
CH23	0~255	Backlight Red: Dark to Bright
CH24	0~255	Backlight Green: Dark to Bright
CH25	0~255	Backlight Blue: Dark to Bright