

Acue Lighting Pixel 16 LED Bar

DMX 2 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	7~255	Strobe: Slow to fast

DMX 4 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	1-4 Dimmer: 0-100%
CH2	0~255	5-8 Dimmer: 0-100%
CH3	0~255	9-12 Dimmer: 0-100%
CH4	0~255	13-16 Dimmer: 0-100%

DMX 8 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	1-2 Dimmer: 0-100%
CH2	0~255	3-4 Dimmer: 0-100%
CH3	0~255	5-6 Dimmer: 0-100%
CH4	0~255	7-8 Dimmer: 0-100%
CH5	0~255	9-10 Dimmer: 0-100%
CH6	0~255	11-12 Dimmer: 0-100%
CH7	0~255	13-14 Dimmer: 0-100%
CH8	0~255	15-16 Dimmer: 0-100%

DMX 16 Channel

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	1 Dimmer: 0-100%
CH2	0~255	2 Dimmer: 0-100%
CH3	0~255	3 Dimmer: 0-100%
CH4	0~255	4 Dimmer: 0-100%
CH5	0~255	5 Dimmer: 0-100%

CH6	0~255	6 Dimmer: 0-100%
CH7	0~255	7 Dimmer: 0-100%
CH8	0~255	8 Dimmer: 0-100%
CH9	0~255	9 Dimmer: 0-100%
CH10	0~255	10 Dimmer: 0-100%
CH11	0~255	11 Dimmer: 0-100%
CH12	0~255	12 Dimmer: 0-100%
CH13	0~255	13 Dimmer: 0-100%
CH14	0~255	14 Dimmer: 0-100%
CH15	0~255	15 Dimmer: 0-100%
CH16	0~255	16 Dimmer: 0-100%

<u>DMX 20 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	7~255	Strobe: Slow to Fast
CH3	BUILT-IN PROGRAMS	
	0~10	No Effect
	11~20	Effect 1
	21~40	Effect 2
	41~60	Effect 3
	61~80	Effect 4
	81~100	Effect 5
	101~120	Effect 6
	121~140	Effect 7
	141~160	Effect 8
	161~180	Effect 9
	181~200	Effect 10
	201~220	Effect 11
	221~240	Effect 12
241~250	Effect 13	
	251~255	Sound Active
CH4	0~255	Effect Speed: Slow to Fast
CH5	0~255	1 Dimmer: 0-100%
CH6	0~255	2 Dimmer: 0-100%
CH7	0~255	3 Dimmer: 0-100%
CH8	0~255	4 Dimmer: 0-100%
CH9	0~255	5 Dimmer: 0-100%
CH10	0~255	6 Dimmer: 0-100%
CH11	0~255	7 Dimmer: 0-100%
CH12	0~255	8 Dimmer: 0-100%
CH13	0~255	9 Dimmer: 0-100%
CH14	0~255	10 Dimmer: 0-100%
CH15	0~255	11 Dimmer: 0-100%
CH16	0~255	12 Dimmer: 0-100%
CH17	0~255	13 Dimmer: 0-100%
CH18	0~255	14 Dimmer: 0-100%
CH19	0~255	15 Dimmer: 0-100%
CH20	0~255	16 Dimmer: 0-100%