

Acue Lighting Pixel 8

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
	DMX 2 Channel mode 1	
	0~11	NA
	12~23	Red
	24~35	Green
	36~47	Blue
	48~59	Yellow

Ch1

60~71	Purple
72~83	Cyan
84~95	White
96~107	Program effect 1
108~119	Program effect 2
120~132	Program effect 3
133~143	Program effect 4
144~155	Program effect 5
156~167	Program effect 6
168~179	Program effect 7
180~191	Program effect 8
192~203	Program effect 9
204~217	Program effect 10
218~227	Program effect 11
228~239	Program effect 12
240~251	Program effect 13
252~255	Sound effect

Ch2	000~255	Speed from slow to fast
DMX 3 Channel mode 2		
Ch1	0~255	Red
Ch2	0~255	Green
Ch3	0~255	Blue
DMX 4 Channel mode 3		
Ch1	0~255	Red
Ch2	0~255	Green
Ch3	0~255	Blue
Ch4	0~255	R, G, B, Dimmer
DMX 14 Channel mode 4		
Ch1	0~255	Red1
Ch2	0~255	Green1
Ch3	0~255	Blue1
Ch4	0~255	Red2

Ch5	0~255	Green2
Ch6	0~255	Blue2
Ch7	0~255	Red3
Ch8	0~255	Green3
Ch9	0~255	Blue3
Ch10	0~255	Red4
Ch11	0~255	Green4
Ch12	0~255	Blue4
Ch13	0~255	Strobe
Ch14	0~255	Master Dimmer
DMX 7 Channel mode 5		
Ch1	0~255	Red
Ch2	0~255	Green
Ch3	0~255	Blue
	0~11	Na
	12~23	Red

Ch4

24~35
36~47
48~59
60~71
72~83
84~95
96~107
108~119
120~132
133~143
144~155
156~167
168~179
180~191
192~203
204~217
218~227
228~239
240~251
252~255

Green
Blue
Yellow
Purple
Cyan
White
Program effect 1
Program effect 2
Program effect 3
Program effect 4
Program effect 5
Program effect 6
Program effect 7
Program effect 8
Program effect 9
Program effect 10
Program effect 11
Program effect 12
Program effect 13
Sound effect

Ch5	0~255	Speed from slow to fast
Ch6	0~255	Strobe
Ch7	0~255	Master dimmer
DMX 26 Channel mode 5		
Ch1	0~255	R1 Dimmer from dark to bright
Ch2	0~255	G1 Dimmer from dark to bright
Ch3	0~255	B1 Dimmer from dark to bright
Ch4	0~255	R2 Dimmer from dark to bright
Ch5	0~255	G2 Dimmer from dark to bright
Ch6	0~255	B2 Dimmer from dark to bright
Ch7	0~255	R3 Dimmer from dark to bright
Ch8	0~255	G3 Dimmer from dark to bright
Ch9	0~255	B3 Dimmer from dark to bright
Ch10	0~255	R4 Dimmer from dark to bright
Ch11	0~255	G4 Dimmer from dark to bright
Ch12	0~255	B4 Dimmer from dark to bright

Ch13	0~255	R5 Dimmer from dark to bright
Ch14	0~255	G5 Dimmer from dark to bright
Ch15	0~255	B5 Dimmer from dark to bright
Ch16	0~255	R6 Dimmer from dark to bright
Ch17	0~255	G6 Dimmer from dark to bright
Ch18	0~255	B6 Dimmer from dark to bright
Ch19	0~255	R7 Dimmer from dark to bright
Ch20	0~255	G7 Dimmer from dark to bright
Ch21	0~255	B7 Dimmer from dark to bright
Ch22	0~255	R8 Dimmer from dark to bright
Ch23	0~255	G8 Dimmer from dark to bright
Ch24	0~255	B8 Dimmer from dark to bright
Ch25	0~255	Strobe
Ch26	0~255	Master dimmer