

# Acue Lighting COB 60W

<b>DMX 3 Channel Model(A001)</b>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	R Dimmer: Dark to Bright
Channel 2	0~255	G Dimmer: Dark to Bright
Channel 3	0~255	B Dimmer: Dark to Bright

<b>DMX 7 Channel Model(D001)</b>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Master Dimmer: Dark to Bright
Channel 2	0~255	R Dimmer: Dark to Bright
Channel 3	0~255	G Dimmer: Dark to Bright
Channel 4	0~255	B Dimmer: Dark to Bright
Channel 5	0~255	Shutter Strobe Speed: Slow to Fast
Channel 6	0~50	No Function
	51~100	Color Selection
	101~150	Colors jump change
	151~200	Color Fade
	201~250	Color Pulse Change
	251~255	Sound-active
Channel 7	0~255	Function Speed: Slow to Fast