

Acue Lighting Pixel 24

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
	DMX 2 Channel A	
	0~11	NA
	12~23	Red
	24~35	Green
	36~47	Blue
	48~59	Yellow

Ch1

60~71	Purple
72~83	Cyan
84~95	White
96~107	Program effect 1
108~119	Program effect 2
120~132	Program effect 3
133~143	Program effect 4
144~155	Program effect 5
156~167	Program effect 6
168~179	Program effect 7
180~191	Program effect 8
192~203	Program effect 9
204~217	Program effect 10
218~227	Program effect 11
228~239	Program effect 12
240~251	Program effect 13
252~255	Sound effect

Ch2	000~255	Speed from slow to fast
Ch1 Ch2 Ch3	DMX 3 Channel C	
	0~255	Red
	0~255	Green
	0~255	Blue
Ch1 Ch2 Ch3 Ch4	DMX 4 Channel D	
	0~255	R, G, B, Dimmer
	0~255	Red
	0~255	Green
	0~255	Blue
Ch1 Ch2 Ch3 Ch4	DMX 6 Channel E	
	0~255	Red1
	0~255	Green1
	0~255	Blue1
	0~255	Red2

Ch5	0~255	Green2
Ch6	0~255	Blue2
Ch1 Ch2 Ch3 Ch4 Ch5	DMX 7 Channel H	
	0~255	R, G, B, Dimmer
	0~255	Red
	0~255	Green
	0~255	Blue
	0~255	RGB Strob
	0~11	Na
	12~23	Red
	24~35	Green
	36~47	Blue
	48~59	Yellow
	60~71	Purple
	72~83	Cyan
	84~95	White
	96~107	Program effect 1

Ch6	108~119	Program effect 2
	120~132	Program effect 3
	133~143	Program effect 4
	144~155	Program effect 5
	156~167	Program effect 6
	168~179	Program effect 7
	180~191	Program effect 8
	192~203	Program effect 9
	204~217	Program effect 10
	218~227	Program effect 11
	228~239	Program effect 12
	240~251	Program effect 13
	252~255	Sound effect
Ch7	0~255	Speed from slow to fast
DMX 12 Channel L		
Ch1	0~255	R1 Dimmer from dark to bright
Ch2	0~255	G1 Dimmer from dark to bright
Ch3	0~255	B1 Dimmer from dark to bright

Ch4	0~255	R2 Dimmer from dark to bright
Ch5	0~255	G2 Dimmer from dark to bright
Ch6	0~255	B2 Dimmer from dark to bright
Ch7	0~255	R3 Dimmer from dark to bright
Ch8	0~255	G3 Dimmer from dark to bright
Ch9	0~255	B3 Dimmer from dark to bright
Ch10	0~255	R4 Dimmer from dark to bright
Ch11	0~255	G4 Dimmer from dark to bright
Ch12	0~255	B4 Dimmer from dark to bright
DMX 24 Channel P		
Ch1	0~255	R1 Dimmer from dark to bright
Ch2	0~255	G1 Dimmer from dark to bright
Ch3	0~255	B1 Dimmer from dark to bright
Ch4	0~255	R2 Dimmer from dark to bright
Ch5	0~255	G2 Dimmer from dark to bright

Ch6	0~255	B2 Dimmer from dark to bright
Ch7	0~255	R3 Dimmer from dark to bright
Ch8	0~255	G3 Dimmer from dark to bright
Ch9	0~255	B3 Dimmer from dark to bright
Ch10	0~255	R4 Dimmer from dark to bright
Ch11	0~255	G4 Dimmer from dark to bright
Ch12	0~255	B4 Dimmer from dark to bright
Ch13	0~255	R5 Dimmer from dark to bright
Ch14	0~255	G5 Dimmer from dark to bright
Ch15	0~255	B5 Dimmer from dark to bright
Ch16	0~255	R6 Dimmer from dark to bright
Ch17	0~255	G6 Dimmer from dark to bright
Ch18	0~255	B6 Dimmer from dark to bright
Ch19	0~255	R7 Dimmer from dark to bright
Ch20	0~255	G7 Dimmer from dark to bright
Ch21	0~255	B7 Dimmer from dark to bright

Ch22	0~255	R8 Dimmer from dark to bright
Ch23	0~255	G8 Dimmer from dark to bright
Ch24	0~255	B8 Dimmer from dark to bright