

Acue Lighting Spider 2 Moving Head

<u>DMX 11 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Pan: 0-540°
CH2	0~255	Tilt Motor 1: 0-∞°
CH3	0~255	Tilt Motor 2: 0-∞°
CH4	0~255	Master Dimmer: 0-100%
CH5	STROBE	
	0~9	No Function
	10~255	
CH6	0~255	R Dimmer: 0-100%
CH7	0~255	G Dimmer: 0-100%
CH8	0~255	B Dimmer: 0-100%
CH9	0~255	W Dimmer: 0-100%
CH10	BUILT-IN EFFECTS	
	0~7	No Function
	8~17	Effect 1
	18~27	Effect 2
	28~37	Effect 3
	38~47	Effect 4
	48~57	Effect 5
	58~67	Effect 6
	68~77	Effect 7
	78~87	Effect 8
	88~97	Effect 9
	98~107	Effect 10
	108~117	Effect 11
	118~127	Effect 12
	128~136	Effect 13
	137~146	Effect 14
	147~156	Effect 15
	157~166	Effect 16
	167~176	Effect 17
	177~186	Effect 18
	187~196	Effect 19
	197~206	Effect 20
	207~216	Effect 21
	217~226	Effect 22
	227~236	Effect 23
237~246	Effect 24	
247~255	Effect 25	
CH11	0~255	Effect Speed

<u>DMX 37 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Pan: 0-540°

CH2	0~255	Tilt Motor 1: 0-∞°
CH3	0~255	Tilt Motor 2: 0-∞°
CH4	0~255	Master Dimmer: 0-100%
CH5	STROBE	
	0~9	No Function
	10~255	
CH6	0~255	R Dimmer 1: 0-100%
CH7	0~255	G Dimmer 1: 0-100%
CH8	0~255	B Dimmer 1: 0-100%
CH9	0~255	W Dimmer 1: 0-100%
CH10	0~255	R Dimmer 2: 0-100%
CH11	0~255	G Dimmer 2: 0-100%
CH12	0~255	B Dimmer 2: 0-100%
CH13	0~255	W Dimmer 2: 0-100%
CH14	0~255	R Dimmer 3: 0-100%
CH15	0~255	G Dimmer 3: 0-100%
CH16	0~255	B Dimmer 3: 0-100%
CH17	0~255	W Dimmer 3: 0-100%
CH18	0~255	R Dimmer 4: 0-100%
CH19	0~255	G Dimmer 4: 0-100%
CH20	0~255	B Dimmer 4: 0-100%
CH21	0~255	W Dimmer 4: 0-100%
CH22	0~255	R Dimmer 5: 0-100%
CH23	0~255	G Dimmer 5: 0-100%
CH24	0~255	B Dimmer 5: 0-100%
CH25	0~255	W Dimmer 5: 0-100%
CH26	0~255	R Dimmer 6: 0-100%
CH27	0~255	G Dimmer 6: 0-100%
CH28	0~255	B Dimmer 6: 0-100%
CH29	0~255	W Dimmer 6: 0-100%
CH30	0~255	R Dimmer 7: 0-100%
CH31	0~255	G Dimmer 7: 0-100%
CH32	0~255	B Dimmer 7: 0-100%
CH33	0~255	W Dimmer 7: 0-100%
CH34	0~255	R Dimmer 8: 0-100%
CH35	0~255	G Dimmer 8: 0-100%
CH36	0~255	B Dimmer 8: 0-100%
CH37	0~255	W Dimmer 8: 0-100%