

Acue Lighting Storm LED 1500W RGB Strobe

DMX 18 Channel		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Master Dimmer
Channel 2	0~255	Red 1
Channel 3	0~255	Red 2
Channel 4	0~255	Red 3
Channel 5	0~255	Red 4
Channel 6	0~255	Green 1
Channel 7	0~255	Green 2
Channel 8	0~255	Green 3
Channel 9	0~255	Green 4
Channel 10	0~255	White 1
Channel 11	0~255	White 2
Channel 12	0~255	White 3
Channel 13	0~255	White 4
Channel 14	0~255	Flash: Slow to Fast
Channel 15	0~255	Flash
Channel 16	0~255	Random Strobe
Channel 17	0~255	Special Effect
Channel 18	0~255	Effect Speed: Slow to Fast

DMX 3 Channel		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Red Dimmer
Channel 2	0~255	Green Dimmer
Channel 3	0~255	Blue Dimmer

DMX 6 Channel		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~255	Master Dimmer
Channel 2	0~255	Flash: Slow to Fast
Channel 3	0~255	Flash
Channel 4	0~255	Random Strobe
Channel 5	0~255	Special Effect
Channel 6	0~255	Effect Speed: Slow to Fast

DMX 9 Channel		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
Channel 1	0~127	No Function

	128~255	Master Dimmer
Channel 2	0~255	R Dimmer
Channel 3	0~255	G Dimmer
Channel 4	0~255	B Dimmer
Channel 5	0~255	Flash: Slow to Fast
Channel 6	0~255	Flash
Channel 7	0~255	Random Strobe
Channel 8	0~255	Special Effect
Channel 9	0~255	Effect Speed: Slow to Fast