

Acue Lighting Stromy 3000CC RGBW

DMX 13 Channel

| <u>Channel</u> | <u>DMX Range</u> | <u>Function</u> |
|----------------|------------------|-------------------|
| CH1 | 000~255 | Dimmer 0% to 100% |
| CH2 | 000~255 | Red 0% to 100% |
| CH3 | 000~255 | Green 0% to 100% |
| CH4 | 000~255 | Blue 0% to 100% |

| | | |
|-------------|----------------|---|
| CH5 | 000~255 | White 0% to 100% |
| CH6 | 000~255 | Intensity of strobe from short to long |
| CH7 | 000~255 | Strobe with effect 1 |
| CH8 | 000~255 | Speed of effect 1 fro slow to fast |
| CH9 | 000~255 | Macro |
| CH10 | 000~255 | Red at background: 0% to 100% |
| CH11 | 000~255 | Blue at background: 0% to 100% |
| CH12 | 000~255 | Green at background: 0% to 100% |
| CH13 | 000~255 | White at background: 0% to 100% |