

Acue Lighting 9x10W LED Flat Par

<u>DMX 8 Channel</u>		
<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
CH1	0~255	Master Dimmer: 0-100%
CH2	0~255	R Dimmer: 0-100%
CH3	0~255	G Dimmer: 0-100%
CH4	0~255	B Dimmer: 0-100%
CH5	0~255	W Dimmer: 0-100%
CH6		STROBE
	0	No Function
	1~255	Speed: Slow to Fast
CH7		MACROS
CH8	1~29	4 Color Jump
	30~59	Full Color Jump
	60~89	Full Color Gradient
	90~119	Variable Pulse
	120~149	Jump, Gradient & Variable Pulse Combination
	150~179	Gradient Strobe
	180~199	Save Disabled
	200~243	Color Selection
	244~245	Restart Effect
	246~250	Sound-Active: Jump
251~255	Sound-Active: Strobe	