

Acue Lighting Color Tube

<u>Channel</u>	<u>DMX Range</u>	<u>Function</u>
DMX 8 Channel Mode		
Ch1	000-255	0-100% Linear Dimming Control
Ch2	000-255	Red Dimming control from 0-100%
Ch3	000-255	Green Dimming control from 0-100%
Ch4	000-255	Blue Dimming control from 0-100%
Ch5	000-255	Strobe Control from 0-100%
Ch6	000-255	Macros control 1
Ch7	000-255	Macros control 2
Ch8	000-255	Macros speed control slow to fast
DMX 14 Channel Mode		
Ch1	0-255	0-100% Linear Global Dimming Control
Ch2	0-255	Strobe Control from 0-100%
Ch3	0-19	No Function
	20-27	First line dimming control
	128-235	Second line dimming control
	236-255	Both lines dimming control
Ch4	0-45	First Stage : No Function
	46-75	First Stage : Red
	76-105	First Stage : Green
	106-135	First Stage : Blue

Ch4	136-165	First Stage : Red/Green
	166-195	First Stage : Red/Blue
	196-225	First Stage : Green/Blue
	226-255	First Stage : Red/Green/Blue
Ch5	0-45	Second Stage : No Function
	46-75	Second Stage : Red
	76-105	Second Stage : Green
	106-135	Second Stage : Blue
	136-165	Second Stage : Red/Green
	166-195	Second Stage : Red/Blue
	196-225	Second Stage : Green/Blue
	226-255	Second Stage : Red/Green/Blue
Ch6	0-45	Third Stage : No Function
	46-75	Third Stage : Red
	76-105	Third Stage : Green
	106-135	Third Stage : Blue
	136-165	Third Stage : Red/Green
	166-195	Third Stage : Red/Blue
	196-225	Third Stage : Green/Blue
	226-255	Third Stage : Red/Green/Blue
Ch7	0-45	Fourth Stage : No Function
	46-75	Fourth Stage : Red
	76-105	Fourth Stage : Green
	106-135	Fourth Stage : Blue
	136-165	Fourth Stage : Red/Green
	166-195	Fourth Stage : Red/Blue
	196-225	Fourth Stage : Green/Blue
	226-255	Fourth Stage : Red/Green/Blue
	0-45	Fifth Stage : No Function

Ch8	46-75	Fifth Stage : Red
	76-105	Fifth Stage : Green
	106-135	Fifth Stage : Blue
	136-165	Fifth Stage : Red/Green
	166-195	Fifth Stage : Red/Blue
	196-225	Fifth Stage : Green/Blue
	226-255	Fifth Stage : Red/Green/Blue
Ch9	0-45	Sixth Stage : No Function
	46-75	Sixth Stage : Red
	76-105	Sixth Stage : Green
	106-135	Sixth Stage : Blue
	136-165	Sixth Stage : Red/Green
	166-195	Sixth Stage : Red/Blue
	196-225	Sixth Stage : Green/Blue
226-255	Sixth Stage : Red/Green/Blue	
Ch10	0-45	Seventh Stage : No Function
	46-75	Seventh Stage : Red
	76-105	Seventh Stage : Green
	106-135	Seventh Stage : Blue
	136-165	Seventh Stage : Red/Green
	166-195	Seventh Stage : Red/Blue
	196-225	Seventh Stage : Green/Blue
226-255	Seventh Stage : Red/Green/Blue	
Ch11	0-45	Eighth Stage : No Function
	46-75	Eighth Stage : Red
	76-105	Eighth Stage : Green
	106-135	Eighth Stage : Blue
	136-165	Eighth Stage : Red/Green
	166-195	Eighth Stage : Red/Blue

	196-225	Eighth Stage : Green/Blue
	226-255	Eighth Stage : Red/Green/Blue
Ch12	0~255	Macros Control 1
Ch13	0~255	Macros Control 2
Ch14	0~255	Macros speed control slow to fast